

# **850 Purchase Order**

**X12/V5010/850 : 850 Purchase Order**

**Version: 1.0 Final**

<b>Company:</b>	<b>Kroger - Health &amp; Wellness</b>
<b>Trading Partner:</b>	<b>Cardinal Health</b>
<b>Modified:</b>	<b>8/17/2018</b>

# Table of Contents

<b>850</b>	<b>Purchase Order</b> .....	<b>1</b>
ISA	Interchange Control Header .....	2
GS	Functional Group Header .....	4
ST	Transaction Set Header .....	6
BEG	Beginning Segment for Purchase Order .....	7
N1	Loop Party Identification .....	8
N1	Party Identification .....	9
PO1	Loop Baseline Item Data .....	10
PO1	Baseline Item Data .....	11
PID	Loop Product/Item Description .....	13
PID	Product/Item Description .....	14
CTT	Loop Transaction Totals .....	15
CTT	Transaction Totals .....	16
SE	Transaction Set Trailer .....	17
GE	Functional Group Trailer .....	18
IEA	Interchange Control Trailer .....	19

# 850 Purchase Order

## Functional Group=PO

**Purpose:** This X12 Transaction Set contains the format and establishes the data contents of the Purchase Order Transaction Set (850) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to the placement of purchase orders for goods and services. This transaction set should not be used to convey purchase order changes or purchase order acknowledgment information.

### Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use

### Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
0100	ST	Transaction Set Header	M	1			Must use
0200	BEG	Beginning Segment for Purchase Order	M	1			Must use

<u>LOOP ID - N1</u>					<u>200</u>	
3100	N1	Party Identification	O	1		Used

### Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<u>LOOP ID - PO1</u>					<u>100000</u>	<u>N2/0100L</u>	
0100	PO1	Baseline Item Data	M	1		N2/0100	Must use
<u>LOOP ID - PID</u>					<u>1000</u>		
0500	PID	Product/Item Description	O	1			Used

### Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<u>LOOP ID - CTT</u>					<u>1</u>	<u>N3/0100L</u>	
0100	CTT	Transaction Totals	O	1		N3/0100	Used
0300	SE	Transaction Set Trailer	M	1			Must use

### Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	GE	Functional Group Trailer	M	1			Must use
	IEA	Interchange Control Trailer	M	1			Must use

### Notes:

2/0100L PO102 is required.

2/0100 PO102 is required.

3/0100L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

3/0100 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

# ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

**User Option (Usage):** Must use

**Purpose:** To start and identify an interchange of zero or more functional groups and interchange-related control segments

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	<b>Authorization Information Qualifier</b>	M	ID	2/2	Must use
<b>Description:</b> Code identifying the type of information in the Authorization Information						
<b>All valid standard codes are used. (Total Codes: 7)</b>						
ISA02	I02	<b>Authorization Information</b>	M	AN	10/10	Must use
<b>Description:</b> Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)						
ISA03	I03	<b>Security Information Qualifier</b>	M	ID	2/2	Must use
<b>Description:</b> Code identifying the type of information in the Security Information						
<b>All valid standard codes are used. (Total Codes: 2)</b>						
ISA04	I04	<b>Security Information</b>	M	AN	10/10	Must use
<b>Description:</b> This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)						
ISA05	I05	<b>Interchange ID Qualifier</b>	M	ID	2/2	Must use
<b>Description:</b> Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified						
<b>All valid standard codes are used. (Total Codes: 41)</b>						
ISA06	I06	<b>Interchange Sender ID</b>	M	AN	15/15	Must use
<b>Description:</b> Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element						
ISA07	I05	<b>Interchange ID Qualifier</b>	M	ID	2/2	Must use
<b>Description:</b> Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified						
<b>All valid standard codes are used. (Total Codes: 41)</b>						
ISA08	I07	<b>Interchange Receiver ID</b>	M	AN	15/15	Must use
<b>Description:</b> Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them						
ISA09	I08	<b>Interchange Date</b>	M	DT	6/6	Must use
<b>Description:</b> Date of the interchange						
ISA10	I09	<b>Interchange Time</b>	M	TM	4/4	Must use

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
		<b>Description:</b> Time of the interchange				
ISA11	I65	<b>Repetition Separator</b>	M		1/1	Must use
		<b>Description:</b> Type is not applicable; the repetition separator is a delimiter and not a data element; this field provides the delimiter used to separate repeated occurrences of a simple data element or a composite data structure; this value must be different than the data element separator, component element separator, and the segment terminator				
ISA12	I11	<b>Interchange Control Version Number</b>	M	ID	5/5	Must use
		<b>Description:</b> Code specifying the version number of the interchange control segments <b>All valid standard codes are used. (Total Codes: 20)</b>				
ISA13	I12	<b>Interchange Control Number</b>	M	N0	9/9	Must use
		<b>Description:</b> A control number assigned by the interchange sender				
ISA14	I13	<b>Acknowledgment Requested</b>	M	ID	1/1	Must use
		<b>Description:</b> Code indicating sender's request for an interchange acknowledgment <b>All valid standard codes are used. (Total Codes: 2)</b>				
ISA15	I14	<b>Interchange Usage Indicator</b>	M	ID	1/1	Must use
		<b>Description:</b> Code indicating whether data enclosed by this interchange envelope is test, production or information <b>All valid standard codes are used. (Total Codes: 3)</b>				
ISA16	I15	<b>Component Element Separator</b>	M		1/1	Must use
		<b>Description:</b> Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator				

# GS Functional Group Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

**User Option (Usage):** Must use

**Purpose:** To indicate the beginning of a functional group and to provide control information

## Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
GS01	479	<b>Functional Identifier Code</b>	M	ID	2/2	Must use
<b>Description:</b> Code identifying a group of application related transaction sets						
<b>CodeList Summary</b> (Total Codes: 260, Included: 1)						
<u>Code</u> <u>Name</u>						
PO Purchase Order (850)						
GS02	142	<b>Application Sender's Code</b>	M	AN	2/15	Must use
<b>Description:</b> Code identifying party sending transmission; codes agreed to by trading partners						
GS03	124	<b>Application Receiver's Code</b>	M	AN	2/15	Must use
<b>Description:</b> Code identifying party receiving transmission; codes agreed to by trading partners						
GS04	373	<b>Date</b>	M	DT	8/8	Must use
<b>Description:</b> Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year						
GS05	337	<b>Time</b>	M	TM	4/8	Must use
<b>Description:</b> Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)						
GS06	28	<b>Group Control Number</b>	M	N0	1/9	Must use
<b>Description:</b> Assigned number originated and maintained by the sender						
GS07	455	<b>Responsible Agency Code</b>	M	ID	1/2	Must use
<b>Description:</b> Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480						
<b>All valid standard codes are used. (Total Codes: 2)</b>						
GS08	480	<b>Version / Release / Industry Identifier Code</b>	M	AN	1/12	Must use
<b>Description:</b> Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed						
<b>CodeList Summary</b> (Total Codes: 54, Included: 1)						

<u>Code</u>	<u>Name</u>
005010	Standards Approved for Publication by ASC X12 Procedures Review Board through October 2003

**Semantics:**

1. GS04 is the group date.
2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

**Comments:**

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

# ST Transaction Set Header

Pos: 0100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

**User Option (Usage):** Must use

**Purpose:** To indicate the start of a transaction set and to assign a control number

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	<b>Transaction Set Identifier Code</b>	M	ID	3/3	Must use
		<b>Description:</b> Code uniquely identifying a Transaction Set <b>All valid standard codes are used. (Total Codes: 318)</b>				
ST02	329	<b>Transaction Set Control Number</b>	M	AN	4/9	Must use
		<b>Description:</b> Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

## Semantics:

1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition. When used, this implementation convention reference takes precedence over the implementation reference specified in the GS08.



# BEG Beginning Segment for Purchase Order

Pos: 0200	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 4

**User Option (Usage):** Must use

**Purpose:** To indicate the beginning of the Purchase Order Transaction Set and transmit identifying numbers and dates

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BEG01	353	Transaction Set Purpose Code	M	ID	2/2	Must use

**Description:** Code identifying purpose of transaction set

**CodeList Summary** (Total Codes: 66, Included: 1)

<u>Code</u>	<u>Name</u>
00	Original

BEG02	92	Purchase Order Type Code	M	ID	2/2	Must use
-------	----	--------------------------	---	----	-----	----------

**Description:** Code specifying the type of Purchase Order

**CodeList Summary** (Total Codes: 76, Included: 1)

<u>Code</u>	<u>Name</u>
NE	New Order

BEG03	324	Purchase Order Number	M	AN	1/22	Must use
-------	-----	-----------------------	---	----	------	----------

**Description:** Identifying number for Purchase Order assigned by the orderer/purchaser

BEG05	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

**Description:** Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

## Semantics:

1. BEG05 is the date assigned by the purchaser to purchase order.

# Loop Party Identification

Pos: 3100	Repeat: 200
Optional	
Loop: N1	Elements: N/A

**User Option (Usage):** Used

**Purpose:** To identify a party by type of organization, name, and code

## Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
3100	N1	Party Identification	O	1		Used

# N1 Party Identification

Pos: 3100	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

**User Option (Usage):** Used

**Purpose:** To identify a party by type of organization, name, and code

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	<b>Entity Identifier Code</b>	M	ID	2/3	Must use
		<b>Description:</b> Code identifying an organizational entity, a physical location, property or an individual				
		<b>CodeList Summary</b> (Total Codes: 1500, Included: 1)				
		<b>Code Name</b>				
		ST		Ship To		
N102	93	<b>Name</b>	X	AN	1/60	Used
		<b>Description:</b> Free-form name				
N103	66	<b>Identification Code Qualifier</b>	X	ID	1/2	Used
		<b>Description:</b> Code designating the system/method of code structure used for Identification Code (67)				
		<b>CodeList Summary</b> (Total Codes: 241, Included: 1)				
		<b>Code Name</b>				
		92		Assigned by Buyer or Buyer's Agent		
N104	67	<b>Identification Code</b>	X	AN	2/80	Used
		<b>Description:</b> Code identifying a party or other code				

## Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

## Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

# Loop Baseline Item Data

Pos: 0100	Repeat: 100000
Mandatory	
Loop: PO1	Elements: N/A

**User Option (Usage):** Must use

**Purpose:** To specify basic and most frequently used line item data

## Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	PO1	Baseline Item Data	M	1		Must use
0500		Loop PID	O		1000	Used

# PO1 Baseline Item Data

Pos: 0100	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 5

**User Option (Usage):** Must use

**Purpose:** To specify basic and most frequently used line item data

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	<b>Assigned Identification</b>	O	AN	1/20	Used
		<b>Description:</b> Alphanumeric characters assigned for differentiation within a transaction set				
PO102	380	<b>Quantity</b>	X	R	1/15	Used
		<b>Description:</b> Numeric value of quantity				
PO103	355	<b>Unit or Basis for Measurement Code</b>	O	ID	2/2	Used
		<b>Description:</b> Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		<b>CodeList Summary</b> (Total Codes: 844, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		UN	Unit			
PO106	235	<b>Product/Service ID Qualifier</b>	X	ID	2/2	Used
		<b>Description:</b> Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		<b>CodeList Summary</b> (Total Codes: 519, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		N4	National Drug Code in 5-4-2 Format			
PO107	234	<b>Product/Service ID</b>	X	AN	1/48	Used
		<b>Description:</b> Identifying number for a product or service				

## Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

## Semantics:

1. PO102 is quantity ordered.

**Comments:**

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

# Loop Product/Item Description

Pos: 0500	Repeat: 1000
Optional	
Loop: PID	Elements: N/A

**User Option (Usage):** Used

**Purpose:** To describe a product or process in coded or free-form format

## Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0500	PID	Product/Item Description	O	1		Used

# PID Product/Item Description

Pos: 0500	Max: 1
Detail - Optional	
Loop: PID	Elements: 2

**User Option (Usage):** Used

**Purpose:** To describe a product or process in coded or free-form format

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID01	349	Item Description Type	M	ID	1/1	Must use

**Description:** Code indicating the format of a description

**CodeList Summary** (Total Codes: 3, Included: 1)

Code Name

F Free-form

PID05	352	Description	X	AN	1/80	Used
-------	-----	-------------	---	----	------	------

**Description:** A free-form description to clarify the related data elements and their content

## Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

## Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

## Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.
3. PID07 specifies the individual code list of the agency specified in PID03.



# Loop Transaction Totals

Pos: 0100	Repeat: 1
Optional	
Loop: CTT	Elements: N/A

**User Option (Usage):** Used

**Purpose:** To transmit a hash total for a specific element in the transaction set

## Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	CTT	Transaction Totals	0	1		Used

# CTT Transaction Totals

Pos: 0100	Max: 1
Summary - Optional	
Loop: CTT	Elements: 1

**User Option (Usage):** Used

**Purpose:** To transmit a hash total for a specific element in the transaction set

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use

**Description:** Total number of line items in the transaction set

## Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

## Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

# SE Transaction Set Trailer

Pos: 0300	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

**User Option (Usage):** Must use

**Purpose:** To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	<b>Number of Included Segments</b>	M	N0	1/10	Must use
		<b>Description:</b> Total number of segments included in a transaction set including ST and SE segments				
SE02	329	<b>Transaction Set Control Number</b>	M	AN	4/9	Must use
		<b>Description:</b> Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

## Comments:

1. SE is the last segment of each transaction set.

# GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

**User Option (Usage):** Must use

**Purpose:** To indicate the end of a functional group and to provide control information

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	<b>Number of Transaction Sets Included</b>	M	N0	1/6	Must use
		<b>Description:</b> Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element				
GE02	28	<b>Group Control Number</b>	M	N0	1/9	Must use
		<b>Description:</b> Assigned number originated and maintained by the sender				

## Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

## Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

# IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

**User Option (Usage):** Must use

**Purpose:** To define the end of an interchange of zero or more functional groups and interchange-related control segments

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	<b>Number of Included Functional Groups</b>	M	N0	1/5	Must use
		<b>Description:</b> A count of the number of functional groups included in an interchange				
IEA02	I12	<b>Interchange Control Number</b>	M	N0	9/9	Must use
		<b>Description:</b> A control number assigned by the interchange sender				