

855 Purchase Order Acknowledgment

X12/V5010/855 : 855 Purchase Order Acknowledgment

Version: 1.0 Final

Company:	Kroger - Health & Wellness
Trading Partner:	Cardinal Health
Modified:	8/21/2018

Table of Contents

855	Purchase Order Acknowledgment	1
ISA	Interchange Control Header	3
GS	Functional Group Header	5
ST	Transaction Set Header	7
BAK	Beginning Segment for Purchase Order Acknowledgment	8
N1	Loop Party Identification	9
N1	Party Identification	10
N3	Party Location	11
N4	Geographic Location	12
PO1	Loop Baseline Item Data	13
PO1	Baseline Item Data	14
PID	Loop Product/Item Description	16
PID	Product/Item Description	17
ACK	Loop Line Item Acknowledgment	18
ACK	Line Item Acknowledgment	19
CTT	Loop Transaction Totals	21
CTT	Transaction Totals	22
SE	Transaction Set Trailer	23
GE	Functional Group Trailer	24
IEA	Interchange Control Trailer	25

855 Purchase Order Acknowledgment

Functional Group=PR

Purpose: This X12 Transaction Set contains the format and establishes the data contents of the Purchase Order Acknowledgment Transaction Set (855) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to a seller's acknowledgment of a buyer's purchase order. This transaction set can also be used as notification of a vendor generated order. This usage advises a buyer that a vendor has or will ship merchandise as prearranged in their partnership.

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
0100	ST	Transaction Set Header	M	1			Must use
0200	BAK	Beginning Segment for Purchase Order Acknowledgment	M	1			Must use

<u>LOOP ID - N1</u>			<u>200</u>		
3000	N1	Party Identification	O	1	Used
3200	N3	Party Location	O	2	Used
3300	N4	Geographic Location	O	1	Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<u>LOOP ID - PO1</u>					<u>100000</u>	<u>N2/0100L</u>	
0100	PO1	Baseline Item Data	O	1		N2/0100	Used
<u>LOOP ID - PID</u>					<u>1000</u>		
0500	PID	Product/Item Description	O	1			Used
<u>LOOP ID - ACK</u>					<u>104</u>		
2700	ACK	Line Item Acknowledgment	O	1			Used

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<u>LOOP ID - CTT</u>					<u>1</u>		
0100	CTT	Transaction Totals	O	1		N3/0100	Used
0300	SE	Transaction Set Trailer	M	1			Must use

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	GE	Functional Group Trailer	M	1			Must use
	IEA	Interchange Control Trailer	M	1			Must use

Notes:

2/0100L PO102 is required.

2/0100 PO102 is required.

3/0100 The number of line items (CTT01) is the accumulation of the number of PO1 segments.

ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

User Option (Usage): Must use

Purpose: To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	Authorization Information Qualifier	M	ID	2/2	Must use
Description: Code identifying the type of information in the Authorization Information						
All valid standard codes are used. (Total Codes: 7)						
ISA02	I02	Authorization Information	M	AN	10/10	Must use
Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)						
ISA03	I03	Security Information Qualifier	M	ID	2/2	Must use
Description: Code identifying the type of information in the Security Information						
All valid standard codes are used. (Total Codes: 2)						
ISA04	I04	Security Information	M	AN	10/10	Must use
Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)						
ISA05	I05	Interchange ID Qualifier	M	ID	2/2	Must use
Description: Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified						
All valid standard codes are used. (Total Codes: 41)						
ISA06	I06	Interchange Sender ID	M	AN	15/15	Must use
Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element						
ISA07	I05	Interchange ID Qualifier	M	ID	2/2	Must use
Description: Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified						
All valid standard codes are used. (Total Codes: 41)						
ISA08	I07	Interchange Receiver ID	M	AN	15/15	Must use
Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them						
ISA09	I08	Interchange Date	M	DT	6/6	Must use
Description: Date of the interchange						
ISA10	I09	Interchange Time	M	TM	4/4	Must use

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
		Description: Time of the interchange				
ISA11	I65	Repetition Separator	M		1/1	Must use
		Description: Type is not applicable; the repetition separator is a delimiter and not a data element; this field provides the delimiter used to separate repeated occurrences of a simple data element or a composite data structure; this value must be different than the data element separator, component element separator, and the segment terminator				
ISA12	I11	Interchange Control Version Number	M	ID	5/5	Must use
		Description: Code specifying the version number of the interchange control segments All valid standard codes are used. (Total Codes: 20)				
ISA13	I12	Interchange Control Number	M	N0	9/9	Must use
		Description: A control number assigned by the interchange sender				
ISA14	I13	Acknowledgment Requested	M	ID	1/1	Must use
		Description: Code indicating sender's request for an interchange acknowledgment All valid standard codes are used. (Total Codes: 2)				
ISA15	I14	Interchange Usage Indicator	M	ID	1/1	Must use
		Description: Code indicating whether data enclosed by this interchange envelope is test, production or information All valid standard codes are used. (Total Codes: 3)				
ISA16	I15	Component Element Separator	M		1/1	Must use
		Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator				

GS Functional Group Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

User Option (Usage): Must use

Purpose: To indicate the beginning of a functional group and to provide control information

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
GS01	479	Functional Identifier Code	M	ID	2/2	Must use
Description: Code identifying a group of application related transaction sets						
CodeList Summary (Total Codes: 260, Included: 1)						
<u>Code</u> <u>Name</u>						
PR Purchase Order Acknowledgment (855)						
GS02	142	Application Sender's Code	M	AN	2/15	Must use
Description: Code identifying party sending transmission; codes agreed to by trading partners						
GS03	124	Application Receiver's Code	M	AN	2/15	Must use
Description: Code identifying party receiving transmission; codes agreed to by trading partners						
GS04	373	Date	M	DT	8/8	Must use
Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year						
GS05	337	Time	M	TM	4/8	Must use
Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)						
GS06	28	Group Control Number	M	N0	1/9	Must use
Description: Assigned number originated and maintained by the sender						
GS07	455	Responsible Agency Code	M	ID	1/2	Must use
Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480						
All valid standard codes are used. (Total Codes: 2)						
GS08	480	Version / Release / Industry Identifier Code	M	AN	1/12	Must use
Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed						
CodeList Summary (Total Codes: 54, Included: 1)						

<u>Code</u>	<u>Name</u>
005010	Standards Approved for Publication by ASC X12 Procedures Review Board through October 2003

Semantics:

1. GS04 is the group date.
2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

ST Transaction Set Header

Pos: 0100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use
		Description: Code uniquely identifying a Transaction Set All valid standard codes are used. (Total Codes: 318)				
ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

Semantics:

1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition. When used, this implementation convention reference takes precedence over the implementation reference specified in the GS08.

BAK Beginning Segment for Purchase Order Acknowledgment

Pos: 0200	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 4

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Acknowledgment Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BAK01	353	Transaction Set Purpose Code	M	ID	2/2	Must use
Description: Code identifying purpose of transaction set						
CodeList Summary (Total Codes: 66, Included: 1)						
<u>Code</u> <u>Name</u>						
06 Confirmation						
BAK02	587	Acknowledgment Type	M	ID	2/2	Must use
Description: Code specifying the type of acknowledgment						
CodeList Summary (Total Codes: 15, Included: 4)						
<u>Code</u> <u>Name</u>						
AC Acknowledge - With Detail and Change						
AD Acknowledge - With Detail, No Change						
AK Acknowledge - No Detail or Change						
RD Reject with Detail						
BAK03	324	Purchase Order Number	M	AN	1/22	Must use
Description: Identifying number for Purchase Order assigned by the orderer/purchaser						
BAK04	373	Date	M	DT	8/8	Must use
Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year						

Semantics:

1. BAK04 is the date assigned by the purchaser to purchase order.

Loop Party Identification

Pos: 3000	Repeat: 200
Optional	
Loop: N1	Elements: N/A

User Option (Usage): Used

Purpose: To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
3000	N1	Party Identification	O	1		Used
3200	N3	Party Location	O	2		Used
3300	N4	Geographic Location	O	1		Used

N1 Party Identification

Pos: 3000	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

User Option (Usage): Used

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

CodeList Summary (Total Codes: 1500, Included: 2)

Code Name

SE Selling Party
ST Ship To

N102	93	Name	X	AN	1/60	Used
------	----	------	---	----	------	------

Description: Free-form name

N103	66	Identification Code Qualifier	X	ID	1/2	Used
------	----	-------------------------------	---	----	-----	------

Description: Code designating the system/method of code structure used for Identification Code (67)

CodeList Summary (Total Codes: 241, Included: 2)

Code Name

91 Assigned by Seller or Seller's Agent
92 Assigned by Buyer or Buyer's Agent

N104	67	Identification Code	X	AN	2/80	Used
------	----	---------------------	---	----	------	------

Description: Code identifying a party or other code

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.

N3 Party Location

Pos: 3200	Max: 2
Heading - Optional	
Loop: N1	Elements: 1

User Option (Usage): Used

Purpose: To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/55	Must use

Description: Address information

N4 Geographic Location

Pos: 3300	Max: 1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Used
		Description: Free-form text for city name				
N402	156	State or Province Code	X	ID	2/2	Used
		Description: Code (Standard State/Province) as defined by appropriate government agency				
N403	116	Postal Code	O	ID	3/15	Used
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				

Syntax Rules:

1. E0207 - Only one of N402 or N407 may be present.
2. C0605 - If N406 is present, then N405 is required.
3. C0704 - If N407 is present, then N404 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

Loop Baseline Item Data

Pos: 0100	Repeat: 100000
Optional	
Loop: PO1 Elements: N/A	

User Option (Usage): Used

Purpose: To specify basic and most frequently used line item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	PO1	Baseline Item Data	O	1		Used
0500		Loop PID	O		1000	Used
2700		Loop ACK	O		104	Used

PO1 Baseline Item Data

Pos: 0100	Max: 1
Detail - Optional	
Loop: PO1	Elements: 8

User Option (Usage): Used

Purpose: To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	Assigned Identification	O	AN	1/20	Used
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
PO102	380	Quantity	X	R	1/15	Used
		Description: Numeric value of quantity				
PO103	355	Unit or Basis for Measurement Code	O	ID	2/2	Used
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		CodeList Summary (Total Codes: 844, Included: 2)				
		<u>Code</u>	<u>Name</u>			
		CA	Case			
		EA	Each			
PO104	212	Unit Price	X	R	1/17	Used
		Description: Price per unit of product, service, commodity, etc.				
PO108	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		CodeList Summary (Total Codes: 519, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		N4	National Drug Code in 5-4-2 Format			
PO109	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				
PO110	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		CodeList Summary (Total Codes: 519, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		VC	Vendor's (Seller's) Catalog Number			
PO111	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.

2. C0504 - If PO105 is present, then PO104 is required.
3. P0809 - If either PO108 or PO109 is present, then the other is required.
4. P1011 - If either PO110 or PO111 is present, then the other is required.

Semantics:

1. PO102 is quantity ordered.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.

Loop Product/Item Description

Pos: 0500	Repeat: 1000
Optional	
Loop: PID	Elements: N/A

User Option (Usage): Used

Purpose: To describe a product or process in coded or free-form format

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0500	PID	Product/Item Description	O	1		Used

PID Product/Item Description

Pos: 0500	Max: 1
Detail - Optional	
Loop: PID	Elements: 2

User Option (Usage): Used

Purpose: To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID01	349	Item Description Type	M	ID	1/1	Must use

Description: Code indicating the format of a description

CodeList Summary (Total Codes: 3, Included: 1)

Code Name

F Free-form

PID05	352	Description	X	AN	1/80	Used
-------	-----	-------------	---	----	------	------

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. R0405 - At least one of PID04 or PID05 is required.
2. C0905 - If PID09 is present, then PID05 is required.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.

Loop Line Item Acknowledgment

Pos: 2700	Repeat: 104
Optional	
Loop: ACK	Elements: N/A

User Option (Usage): Used

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2700	ACK	Line Item Acknowledgment	O	1		Used

ACK Line Item Acknowledgment

Pos: 2700	Max: 1
Detail - Optional	
Loop: ACK	Elements: 7

User Option (Usage): Used

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
ACK01	668	Line Item Status Code	M	ID	2/2	Must use

Description: Code specifying the action taken by the seller on a line item requested by the buyer

CodeList Summary (Total Codes: 26, Included: 5)

Code Name

- IA Item Accepted
- IP Item Accepted - Price Changed
- IQ Item Accepted - Quantity Changed
- IR Item Rejected
- IS Item Accepted - Substitution Made

ACK02	380	Quantity	X	R	1/15	Used
-------	-----	----------	---	---	------	------

Description: Numeric value of quantity

ACK03	355	Unit or Basis for Measurement Code	X	ID	2/2	Used
-------	-----	------------------------------------	---	----	-----	------

Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken

CodeList Summary (Total Codes: 844, Included: 2)

Code Name

- CA Case
- EA Each

ACK09	235	Product/Service ID Qualifier	X	ID	2/2	Used
-------	-----	------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 519, Included: 1)

Code Name

- N4 National Drug Code in 5-4-2 Format

ACK10	234	Product/Service ID	X	AN	1/48	Used
-------	-----	--------------------	---	----	------	------

Description: Identifying number for a product or service

ACK11	235	Product/Service ID Qualifier	X	ID	2/2	Used
-------	-----	------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 519, Included: 1)

Code Name

- VC Vendor's (Seller's) Catalog Number

ACK12	234	Product/Service ID	X	AN	1/48	Used
-------	-----	---------------------------	---	----	------	------

Description: Identifying number for a product or service

Syntax Rules:

1. P0203 - If either ACK02 or ACK03 is present, then the other is required.
2. P0910 - If either ACK09 or ACK10 is present, then the other is required.
3. P1112 - If either ACK11 or ACK12 is present, then the other is required.

Loop Transaction Totals

Pos: 0100	Repeat: 1
Optional	
Loop: CTT	Elements: N/A

User Option (Usage): Used

Purpose: To transmit a hash total for a specific element in the transaction set

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	CTT	Transaction Totals	0	1		Used

CTT Transaction Totals

Pos: 0100 Max: 1
 Summary - Optional
 Loop: CTT Elements: 1

User Option (Usage): Used

Purpose: To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use

Description: Total number of line items in the transaction set

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

SE Transaction Set Trailer

Pos: 0300	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	N0	1/10	Must use
		Description: Total number of segments included in a transaction set including ST and SE segments				
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

Comments:

1. SE is the last segment of each transaction set.

GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	Number of Transaction Sets Included	M	N0	1/6	Must use
		Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element				
GE02	28	Group Control Number	M	N0	1/9	Must use
		Description: Assigned number originated and maintained by the sender				

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	Number of Included Functional Groups	M	N0	1/5	Must use
		Description: A count of the number of functional groups included in an interchange				
IEA02	I12	Interchange Control Number	M	N0	9/9	Must use
		Description: A control number assigned by the interchange sender				